

Calendar, Tasks and Notes Profile (CTN)

Bluetooth® Implementation Conformance Statement (ICS) Proforma

- **Revision:** CTN.ICS.p6
- **Revision Date:** 2026-06-23
- **Prepared By:** Audio, Telephony & Automotive Working Group
- **Published during TCRL:** TCRL.pkg104



This document, regardless of its title or content, is not a Bluetooth Specification as defined in the Bluetooth Patent/Copyright License Agreement (“PCLA”) and Bluetooth Trademark License Agreement. Use of this document by members of Bluetooth SIG is governed by the membership and other related agreements between Bluetooth SIG Inc. (“Bluetooth SIG”) and its members, including the PCLA and other agreements posted on Bluetooth SIG’s website located at www.bluetooth.com.

THIS DOCUMENT IS PROVIDED “AS IS” AND BLUETOOTH SIG, ITS MEMBERS, AND THEIR AFFILIATES MAKE NO REPRESENTATIONS OR WARRANTIES AND DISCLAIM ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING ANY WARRANTY OF MERCHANTABILITY, TITLE, NON-INFRINGEMENT, FITNESS FOR ANY PARTICULAR PURPOSE, THAT THE CONTENT OF THIS DOCUMENT IS FREE OF ERRORS.

TO THE EXTENT NOT PROHIBITED BY LAW, BLUETOOTH SIG, ITS MEMBERS, AND THEIR AFFILIATES DISCLAIM ALL LIABILITY ARISING OUT OF OR RELATING TO USE OF THIS DOCUMENT AND ANY INFORMATION CONTAINED IN THIS DOCUMENT, INCLUDING LOST REVENUE, PROFITS, DATA OR PROGRAMS, OR BUSINESS INTERRUPTION, OR FOR SPECIAL, INDIRECT, CONSEQUENTIAL, INCIDENTAL OR PUNITIVE DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, AND EVEN IF BLUETOOTH SIG, ITS MEMBERS, OR THEIR AFFILIATES HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

This document is proprietary to Bluetooth SIG. This document may contain or cover subject matter that is intellectual property of Bluetooth SIG and its members. The furnishing of this document does not grant any license to any intellectual property of Bluetooth SIG or its members.

This document is subject to change without notice.

Copyright © 2014–2026 by Bluetooth SIG, Inc. The Bluetooth word mark and logos are owned by Bluetooth SIG, Inc. Other third-party brands and names are the property of their respective owners.



Contents

| | | |
|----------|--|-----------|
| 1 | General principles | 4 |
| 1.1 | Implementation Under Test (IUT) identification | 4 |
| 1.2 | Enforcement of inter-layer dependencies | 4 |
| 2 | ICS declarations | 5 |
| 2.1 | Versions | 5 |
| 2.2 | Core Configuration..... | 5 |
| 2.3 | Roles | 5 |
| 2.4 | CTN Client Equipment (CCE) | 5 |
| 2.4.1 | CTN Services..... | 5 |
| 2.4.2 | CTN Profile Features | 6 |
| 2.5 | CTN Server Equipment (CSE)..... | 7 |
| 2.5.1 | CTN Services..... | 7 |
| 2.5.2 | CTN Profile Features | 7 |
| 3 | Requirements Towards Other Bluetooth Layers | 8 |
| 3.1 | GAP requirements | 8 |
| 3.2 | GOEP requirements..... | 8 |
| 3.2.1 | GOEP requirements (CCE)..... | 8 |
| 3.2.2 | GOEP requirements (CSE)..... | 10 |
| 3.3 | SDP requirements..... | 12 |
| 4 | References | 13 |
| 5 | Revision history and acknowledgments | 14 |

1 General principles

1.1 Implementation Under Test (IUT) identification

Using the Bluetooth SIG qualification tool, the implementer is expected to declare details about what will be implemented.

1.2 Enforcement of inter-layer dependencies

This ICS includes one or more tables with inter-layer dependencies (ILDs). ILDs are used for specification requirements that are dependent on other supporting specifications. ILDs can refer to an individual ICS item in a separate layer (individual ILD), or it can refer to the full layer (full-layer ILD).

ILDs residing in an X2Core layer will be enforced from the Bluetooth SIG qualification tool in the following conditions, depending on where the referred ILD is residing:

| Referred ILD resides in | Individual ILD | Full-layer ILD |
|-------------------------|---|---|
| Controller layer | Core-Complete configuration, or Referred layer is supported | N/A |
| Lower HCI layer | HCI is supported | N/A |
| Upper HCI layer | Core-Host configuration, or UHCI is supported | N/A |
| Host layer | Core-Host configuration, or Core-Complete configuration, or Referred layer is supported | N/A |
| X2Core layer | Core-Host configuration, or Core-Complete configuration, or Referred layer is supported | Core-Host configuration, or Core-Complete configuration |

Table 1.1: Enforcement of an ILD within the Bluetooth SIG qualification tool

2 ICS declarations

2.1 Versions

Table 0: X.Y Versions

| Item | Version | Reference | Status |
|------|----------|-----------|----------|
| 1 | CTN v1.0 | [1] | C.1, C.2 |

C.1: Mandatory for this Profile.

C.2: Can only be supported with an active X.Y.Z version after Deprecation or Withdrawal. Deprecated 2028-02-01. Withdrawn 2030-02-01.

Table 0a: X.Y.Z Versions

| Item | Version | Reference | Status |
|------|------------|-----------|--------|
| 1 | CTN v1.0.1 | [1] | C.1 |

C.1: Optional IF CTN 0/1 "CTN v1.0" AND "CTN v1.0" is Not (Deprecated or Withdrawn), otherwise Mandatory IF CTN 0/1 "CTN v1.0" AND "CTN v1.0" is Deprecated or Withdrawn, otherwise Excluded.

2.2 Core Configuration

Table 0b: Core Configuration Requirements

| Item | Core Configuration | Reference | Status |
|------|-------------------------------|-----------|----------|
| 1 | Profile supported over BR/EDR | [1] 2.1 | C.1, C.3 |
| 2 | Profile supported over LE | [1] 2.1 | C.2 |

C.1: Excluded for this Profile IF CORE 41/2 "LE Core Configuration" OR CORE 40/1 "Core-Controller".

C.2: Excluded for this Profile.

C.3: Mandatory for this Profile.

2.3 Roles

Table 1: Role Requirements

| Item | Role | Reference | Status |
|------|----------------------|-----------|--------|
| 1 | CTN Client Equipment | [1] 2.2 | C.1 |
| 2 | CTN Server Equipment | [1] 2.2 | C.1 |

C.1: Mandatory to support at least one.

2.4 CTN Client Equipment (CCE)

2.4.1 CTN Services

Table 2: Supported CTN Services CCE

Prerequisite: CTN 1/1 "CTN Client Equipment"

| Item | Feature | Reference | Status |
|------|---------------------------------------|-----------|--------|
| 1a | CTN Access Service, single account | [1] 3.5 | M |
| 1b | CTN Access Service, multiple accounts | [1] 3.5 | O |



| Item | Feature | Reference | Status |
|------|--------------------------|-----------|--------|
| 2 | CTN Notification Service | [1] 4.3 | O |

2.4.2 CTN Profile Features

Table 3: Supported Features CCE

Prerequisite: CTN 1/1 "CTN Client Equipment"

| Item | Feature | Reference | Status |
|------|-----------------------------|-----------|----------|
| 1 | CTN Account Management | [1] 4.2 | M |
| 1a | GetCTNAccountInformation | [1] 5.9 | M |
| 1b | CTNNotificationRegistration | [1] 5.2 | C.1 |
| 1c | SyncCTNAccount | [1] 5.10 | O |
| 2 | CTN Notification | [1] 4.3 | C.1, C.2 |
| 2a | SendCTNEvent | [1] 5.1 | C.3 |
| 3 | CTN Browsing | [1] 4.4 | C.2 |
| 3a | GetCTNListing | [1] 5.3 | C.4 |
| 4 | CTN Downloading | [1] 4.5 | M |
| 4a | GetCTNObject | [1] 5.4 | M |
| 4b | SetCTNStatus | [1] 5.5 | M |
| 5 | CTN Uploading | [1] 4.6 | O |
| 5a | PushCTNObject | [1] 5.6 | C.5 |
| 6 | CTN Forward | [1] 4.7 | O |
| 6a | ForwardCTN | [1] 5.7 | C.6 |
| 7 | No longer used | N/A | N/A |
| 7a | EVENT | [1] 3.3.1 | C.7 |
| 7b | TASK | [1] 3.3.1 | C.7 |
| 7c | NOTE | [1] 3.3.1 | C.7 |
| 8 | CTN Delete | [1] 4.8 | O |
| 8a | SetCTNStatus | [1] 5.5 | C.8 |

- C.1: Mandatory IF CTN 2/2 "CTN Notification Service", otherwise Excluded.
- C.2: Mandatory to support at least one.
- C.3: Mandatory IF CTN 3/2 "CTN Notification", otherwise Excluded.
- C.4: Mandatory IF CTN 3/3 "CTN Browsing", otherwise Excluded.
- C.5: Mandatory IF CTN 3/5 "CTN Uploading", otherwise Excluded.
- C.6: Mandatory IF CTN 3/6 "CTN Forward", otherwise Excluded.
- C.7: Mandatory to support at least one.
- C.8: Mandatory IF CTN 3/8 "CTN Delete", otherwise Excluded.

2.5 CTN Server Equipment (CSE)

2.5.1 CTN Services

Table 4: Supported CTN Services CSE

Prerequisite: CTN 1/2 "CTN Server Equipment"

| Item | Feature | Reference | Status |
|------|---------------------------------------|-----------|--------|
| 1a | CTN Access Service, single account | [1] 3.5 | M |
| 1b | CTN Access Service, multiple accounts | [1] 3.5 | O |
| 2 | CTN Notification Service | [1] 4.3 | M |

2.5.2 CTN Profile Features

Table 5: Supported Features CSE

Prerequisite: CTN 1/2 "CTN Server Equipment"

| Item | Feature | Reference | Status |
|------|-----------------------------|-----------|--------|
| 1 | CTN Account Management | [1] 4.2 | M |
| 1a | GetCTNAccountInformation | [1] 5.9 | M |
| 1b | CTNNotificationRegistration | [1] 5.2 | M |
| 1c | SyncCTNAccount | [1] 5.10 | O |
| 2 | CTN Notification | [1] 4.3 | M |
| 2a | SendCTNEvent | [1] 5.1 | M |
| 3 | CTN Browsing | [1] 4.4 | M |
| 3a | GetCTNListing | [1] 5.3 | M |
| 4 | CTN Downloading | [1] 4.5 | M |
| 4a | GetCTNObject | [1] 5.4 | M |
| 4b | SetCTNStatus | [1] 5.5 | M |
| 5 | CTN Uploading | [1] 4.6 | M |
| 5a | PushCTNObject | [1] 5.6 | M |
| 6 | CTN Forward | [1] 4.7 | M |
| 6a | ForwardCTN | [1] 5.7 | M |
| 7 | No longer used | N/A | N/A |
| 7a | EVENT | [1] 3.3.1 | C.1 |
| 7b | TASK | [1] 3.3.1 | C.1 |
| 7c | NOTE | [1] 3.3.1 | C.1 |
| 8 | CTN Delete | [1] 4.8 | O |
| 8a | SetCTNStatus | [1] 5.5 | M |

C.1: Mandatory to support at least one.



3 Requirements Towards Other Bluetooth Layers

3.1 GAP requirements

Table 6: GAP Mode Requirements (CCE)

Prerequisite: CTN 1/1 "CTN Client Equipment"

| Item | Feature | Reference | Status | Inter-Layer Dependency |
|------|---------------------------|--------------------|--------|------------------------|
| 1 | General discoverable mode | [1] 6.4, [2] 6.4.1 | C.1 | [3] GAP 1/3 |
| 1a | Limited discoverable mode | [1] 6.4, [2] 6.4.1 | C.1 | [3] GAP 1/2 |
| 2 | Bondable mode | [1] 6.4, [2] 6.4.1 | M | [3] GAP 1/7 |

C.1: Mandatory to support at least one.

Table 7: No longer used

Table 8: GAP Mode Requirements (CSE)

Prerequisite: CTN 1/2 "CTN Server Equipment"

| Item | Feature | Reference | Status | Inter-Layer Dependency |
|------|----------------|--------------------|--------|------------------------|
| 1 | No longer used | N/A | N/A | N/A |
| 2 | Bondable mode | [1] 6.4, [2] 6.4.1 | M | [3] GAP 1/7 |

Table 9: GAP Idle Mode Requirements (CSE)

Prerequisite: CTN 1/2 "CTN Server Equipment"

| Item | Capability | Reference | Status | Inter-Layer Dependency |
|------|-------------------------------|--------------------|--------|------------------------|
| 1 | Initiation of general inquiry | [1] 6.4, [2] 6.4.3 | M | [3] GAP 3/1 |
| 2 | No longer used | N/A | N/A | N/A |
| 3 | Initiation of general bonding | [1] 6.4, [2] 6.1.1 | M | [3] GAP 3/5 |

3.2 GOEP requirements

3.2.1 GOEP requirements (CCE)

Table 10: CCE OBEX Functions Support for CAS

Prerequisite: CTN 1/1 "CTN Client Equipment"

| Item | OBEX Operation | Reference | Status |
|------|---------------------|-----------|--------|
| 1 | Connect (Client) | [1] 6.2.2 | M |
| 2 | Disconnect (Client) | [1] 6.2.2 | M |
| 3 | Put (Client) | [1] 6.2.2 | M |



| Item | OBEX Operation | Reference | Status |
|------|----------------|-----------|--------|
| 4 | Get (Client) | [1] 6.2.2 | M |
| 5 | Abort (Client) | [1] 6.2.2 | M |

Table 11: CCE OBEX Functions Support for CNS

Prerequisite: CTN 1/1 "CTN Client Equipment"

| Item | OBEX Operation | Reference | Status |
|------|---------------------|-----------|--------|
| 1 | Connect (Server) | [1] 6.2.2 | C.1 |
| 2 | Disconnect (Server) | [1] 6.2.2 | C.1 |
| 3 | Put (Server) | [1] 6.2.2 | C.1 |
| 4 | Abort (Server) | [1] 6.2.2 | C.1 |

C.1: Mandatory IF CTN 2/2 "CTN Notification Service", otherwise Optional.

Table 12: CCE OBEX Header Support

Prerequisite: CTN 1/1 "CTN Client Equipment"

| Item | OBEX Header | Reference | Status |
|------|------------------------|-----------|--------|
| 1 | Name | [1] 6.2.3 | M |
| 2 | Type | [1] 6.2.3 | M |
| 3 | Body | [1] 6.2.3 | M |
| 4 | End of Body | [1] 6.2.3 | M |
| 5 | Target | [1] 6.2.3 | M |
| 6 | Who | [1] 6.2.3 | M |
| 7 | Connection ID | [1] 6.2.3 | M |
| 8 | Application Parameters | [1] 6.2.3 | M |
| 9 | SRM | [1] 6.2.3 | M |
| 10 | Receive SRMP | [1] 6.2.3 | M |
| 11 | Send SRMP | [1] 6.2.3 | O |

Table 13: CCE OBEX Client Error Codes Recognition

Prerequisite: CTN 1/1 "CTN Client Equipment"

| Item | OBEX Operation | Reference | Status |
|------|---------------------|----------------------|--------|
| 1 | Bad Request | [1] 6.2.6, [2] 6.2.7 | M |
| 2 | Not Implemented | [1] 6.2.6, [2] 6.2.7 | M |
| 3 | Unauthorized | [1] 6.2.6, [2] 6.2.7 | M |
| 4 | Precondition Failed | [1] 6.2.6, [2] 6.2.7 | M |
| 5 | Not Found | [1] 6.2.6, [2] 6.2.7 | M |
| 6 | Not Acceptable | [1] 6.2.6, [2] 6.2.7 | M |



| Item | OBEX Operation | Reference | Status |
|------|---------------------|----------------------|--------|
| 7 | Service Unavailable | [1] 6.2.6, [2] 6.2.7 | M |
| 8 | Forbidden | [1] 6.2.6, [2] 6.2.7 | M |

Table 14: CCE OBEX Server Error Codes Reporting

Prerequisite: CTN 2/2 "CTN Notification Service"

| Item | OBEX Operation | Reference | Status |
|------|---------------------|----------------------|--------|
| 1 | Bad Request | [1] 6.2.6, [2] 6.2.7 | M |
| 2 | Not Implemented | [1] 6.2.6, [2] 6.2.7 | M |
| 3 | Unauthorized | [1] 6.2.6, [2] 6.2.7 | O |
| 4 | Precondition Failed | [1] 6.2.6, [2] 6.2.7 | O |
| 5 | Not Found | [1] 6.2.6, [2] 6.2.7 | O |
| 6 | Not Acceptable | [1] 6.2.6, [2] 6.2.7 | O |
| 7 | Service Unavailable | [1] 6.2.6, [2] 6.2.7 | O |
| 8 | Forbidden | [1] 6.2.6, [2] 6.2.7 | O |

3.2.2 GOEP requirements (CSE)

Table 15: CSE OBEX Functions Support for CAS

Prerequisite: CTN 1/2 "CTN Server Equipment"

| Item | OBEX Operation | Reference | Status |
|------|---------------------|-----------|--------|
| 1 | Connect (Server) | [1] 6.2.2 | M |
| 2 | Disconnect (Server) | [1] 6.2.2 | M |
| 3 | Put (Server) | [1] 6.2.2 | M |
| 4 | Get (Server) | [1] 6.2.2 | M |
| 5 | Abort (Server) | [1] 6.2.2 | M |
| 6 | No longer used | N/A | N/A |

Table 16: CSE OBEX Functions Support for CNS

Prerequisite: CTN 1/2 "CTN Server Equipment"

| Item | OBEX Operation | Reference | Status |
|------|---------------------|-----------|--------|
| 1 | Connect (Client) | [1] 6.2.2 | M |
| 2 | Disconnect (Client) | [1] 6.2.2 | M |
| 3 | Put (Client) | [1] 6.2.2 | M |
| 4 | Abort (Client) | [1] 6.2.2 | M |



Table 17: CSE OBEX Header Support*Prerequisite: CTN 1/2 "CTN Server Equipment"*

| Item | OBEX Header | Reference | Status |
|------|------------------------|-----------|--------|
| 1 | Name | [1] 6.2.3 | M |
| 2 | Type | [1] 6.2.3 | M |
| 3 | Body | [1] 6.2.3 | M |
| 4 | End of Body | [1] 6.2.3 | M |
| 5 | Target | [1] 6.2.3 | M |
| 6 | Who | [1] 6.2.3 | M |
| 7 | Connection ID | [1] 6.2.3 | M |
| 8 | Application Parameters | [1] 6.2.3 | M |
| 9 | SRM | [1] 6.2.3 | M |
| 10 | Receive SRMP | [1] 6.2.3 | M |
| 11 | Send SRMP | [1] 6.2.3 | O |

Table 18: CSE OBEX Client Error Codes Recognition*Prerequisite: CTN 1/2 "CTN Server Equipment"*

| Item | OBEX Operation | Reference | Status |
|------|---------------------|----------------------|--------|
| 1 | Bad Request | [1] 6.2.6, [2] 6.2.7 | M |
| 2 | Not Implemented | [1] 6.2.6, [2] 6.2.7 | M |
| 3 | Unauthorized | [1] 6.2.6, [2] 6.2.7 | M |
| 4 | Precondition Failed | [1] 6.2.6, [2] 6.2.7 | M |
| 5 | Not Found | [1] 6.2.6, [2] 6.2.7 | M |
| 6 | Not Acceptable | [1] 6.2.6, [2] 6.2.7 | M |
| 7 | Service Unavailable | [1] 6.2.6, [2] 6.2.7 | M |
| 8 | Forbidden | [1] 6.2.6, [2] 6.2.7 | M |

Table 19: CSE OBEX Server Error Codes Reporting*Prerequisite: CTN 4/2 "CTN Notification Service"*

| Item | OBEX Operation | Reference | Status |
|------|---------------------|----------------------|--------|
| 1 | Bad Request | [1] 6.2.6, [2] 6.2.7 | M |
| 2 | Not Implemented | [1] 6.2.6, [2] 6.2.7 | M |
| 3 | Unauthorized | [1] 6.2.6, [2] 6.2.7 | O |
| 4 | Precondition Failed | [1] 6.2.6, [2] 6.2.7 | O |
| 5 | Not Found | [1] 6.2.6, [2] 6.2.7 | O |
| 6 | Not Acceptable | [1] 6.2.6, [2] 6.2.7 | O |
| 7 | Service Unavailable | [1] 6.2.6, [2] 6.2.7 | O |
| 8 | Forbidden | [1] 6.2.6, [2] 6.2.7 | O |



3.3 SDP requirements

Table 20: SDP Requirements (CCE)

Prerequisite: CTN 1/1 "CTN Client Equipment"

| Item | Feature | Reference | Status | Inter-Layer Dependency |
|------|--------------------------------|-----------|--------|------------------------|
| 1 | ProtocolDescriptorList | [1] 7.3 | M | [4] SDP 9/2 |
| 2 | BluetoothProfileDescriptorList | [1] 7.3 | M | [4] SDP 9/14 |
| 3 | ServiceName | [1] 7.3 | M | [4] SDP 9/9 |

Table 21: SDP Requirements (CSE)

Prerequisite: CTN 1/2 "CTN Server Equipment"

| Item | Feature | Reference | Status | Inter-Layer Dependency |
|------|--------------------------------|-----------|--------|------------------------|
| 1 | ProtocolDescriptorList | [1] 7.2 | M | [4] SDP 9/2 |
| 2 | BluetoothProfileDescriptorList | [1] 7.2 | M | [4] SDP 9/14 |
| 3 | ServiceName | [1] 7.2 | M | [4] SDP 9/9 |

4 References

- [1] Bluetooth Calendar, Tasks and Notes Profile Specification, Version 1.0 or later
- [2] Bluetooth Profile Generic PIM Profile Specification, Version 1.0 or later
- [3] ICS Proforma for Generic Access Profile (GAP)
- [4] ICS Proforma for Service Discovery Protocol (SDP)

5 Revision history and acknowledgments

Revision History

| Publication Number | Revision Number | Date | Comments |
|--------------------|-----------------|----------------------------|--|
| 0 | 1.0.0 | 2014-09-18 | Approved by BoD |
| | 1.0.1r00 | 2017-10-08 | TSE 9955 (rating 1): Updated template. Removed General Statement of Conformance section. Removed table number fields. Fixed tables in Section 2 to conform to the current template conventions. |
| 1 | 1.0.1 | 2018-07-01 | Approved by BTI. Prepared for TCRL 2018-1 publication. |
| | 1.0.1.0r00 | 2018-11-09 | Updated version number to 1.0.1.0 to align with adoption of the specification 1.0.1. Added Table 0a and item 0a/1 for the new version. |
| 2 | 1.0.1.0 | 2018-11-21 | Approved by BTI. Prepared for TCRL 2018-2 publication. |
| | p3r00–r02 | 2023-10-12 – 2023-11-20 | <p>TSE 19241 (rating 1): Made editorial edits to align the document with the latest ICS template, including updates to the IUT identification section, table titles, and spacing. Removed Support columns and “is supported” language. Updated C.1 for Tables 1 and 5. Updated the prerequisite for Tables 2–21. In Table 3, updated C.1–C.8. In Table 6, added an ILD column, deleted unnecessary headings within the table, updated the Reference and Status values for Item 1, added Item 1a, updated the Feature and Reference values for Item 2, and updated C.1. Marked Table 7 as no longer used. In Table 8, added an ILD column, deleted unnecessary headings within the table, marked Item 1 as no longer used, and updated the Reference value for Item 2. In Table 9, added an ILD column, updated the Reference value for Item 1, marked Item 2 as no longer used, updated the Reference and Status values for Item 3, and deleted C.1. Deleted an introductory statement for Section 2.2. In Table 10, updated the references and deleted C.1. In Table 11, updated the Reference values and updated C.1. In Tables 12, 13, 16, 17, and 19, updated the Reference values. In Tables 14 and 18, updated the Reference values and updated all values for Item 5. In Table 15, updated the Reference values and marked Item 6 as no longer used. In Tables 20 and 21, added an ILD column and updated the Reference values. Updated the references.</p> <p>Replaced the Bluetooth logo in the footer and updated the copyright page to align with the latest version of the DNMD. Created separate sections for Roles and Versions. Moved the revision history and acknowledgments to the end of the document. Added a Publication Number column to the Revision History. Revised the document numbering convention, setting the last release publication of 1.0.1.0 as p2.</p> |

| Publication Number | Revision Number | Date | Comments |
|--------------------|-----------------|-------------------------|---|
| 3 | p3 | 2024-07-01 | Approved by BTI on 2024-05-22. Prepared for TCRL 2024-1 publication. |
| | p4r00 | 2025-02-24 | TSE 26902 (rating 2): Added "Core Configuration" section and Table 0b. Updated 3/7 and 5/7. Applied current ICS template. Deleted draft revision history comments prior to p0. |
| 4 | p4 | 2025-07-08 | Approved by BTI on 2025-05-30. Prepared for TCRL pkg100 publication. |
| | p5r00 | 2025-12-05 – 2026-01-07 | TSE 28346 (rating 1): Updated the conditions in the transport table to make sure the layer is excluded when the design is an implementation of the Core-Controller Configuration by adding "OR CORE 40/1 "Core-Controller"" to an already excluded transport based on Core Configuration support. |
| 5 | p5 | 2026-02-17 | Approved by BTI on 2026-01-22. Prepared for TCRL pkg102 publication. |
| | p6r00 | 2026-03-09 | 28653 (rating 1): Applied 2024 BoD resolution for D&W to CTN 1.0. Changed status of 0/1 (CTN v1.0) and added two new conditionals (C.1, C.2). Updated C.1 for 0a (CTN v1.0.1) to reflect CTN v1.0 D&W status. |
| 6 | p6 | 2026-06-23 | Approved by BTI on 2026-05-28. Prepared for TCRL pkg104 publication. |

Acknowledgments

| Name | Company |
|---------------------|----------------|
| Veit Kötting | Berner&Mattner |
| Joachim Mertz | Berner&Mattner |
| Dominik Sollfrank | Berner&Mattner |
| Alicia Courtney | Broadcom |
| Kyle Penri-Williams | Parrot |